Review: ABCs of Networks

- Starting Point: Send bits between 2 computers



- Queue on each end
- Can send both ways ("Full Duplex")
- Rules for communication? "protocol"
  - Inside a computer?
  - Loads/Stores: Request(Address) & Response (Data)
  - Need Request & Response
  - Name for standard group of bits sent: Packet

© Patterson 1994

Review: Questions about Simple Network

- What if more than 2 computers want to communicate?
  - Need computer address field in packet?
- What if packet is garbled in transit?
  - Add error detection field in packet?
- What if packet is lost?
  - More elaborate protocols to detect loss?
- What if multiple processes/machine?
  - Queue per process?
- Questions such as these lead to more complex protocols and packet formats

© Patterson 1994

Review: Interconnect Issues

- Implementation Issues
- Performance Measures
- Architecutal Issues
- Practical Issues

© Patterson 1994

Review: Implementation Issues

Interconnect	*MPP*	*LAN*	*WAN*
Example	CM-5	Ethernet	ATM
Maximum length between nodes	25 m	500 m; ≤5 repeaters	copper: 100 m optical: 1000 m
Number data lines	4	1	1
Clock Rate	40 MHz	10 MHz	≥ 155.5 MHz
Shared vs. Switch	Switch	Shared	Switch
Maximum number of nodes	2048	254	> 10,000
Media Material	Copper	Twisted pair copper wire or Coaxial cable	Twisted pair copper wire or optical fiber

© Patterson 1994

Review: Network Performance Measures



- **Overhead: latency of interface vs. Latency: network**

© Patterson 1994

Review: Impact of Overhead on Delivered BW



- **BW model: Time = overhead + msg size/peak BW**
- **> 50% data transfered in packets = 8KB**

© Patterson 1994

Architectural Options

Interconnect	*MPP*	*LAN*	*WAN*
Example	CM-5	Ethernet	ATM
Topology	"Fat" tree	Line	Variable, constructed from multistage switches
Connection based?	No	No	Yes
Data Transfer Size	Variable: 4 to 20B	Variable: 0 to 1500B	Fixed: 48B
Store & Forward?	No	n.a.	Yes
Congestion control	At source: Flow control via back pressure	At source: Listen for E-net idle	Rate based via choke packets

© Patterson 1994

Topology

- Structure of the interconnect
- Determines
  - degree: number of links from a node
  - diameter: max number of links crossed between nodes
  - average distance: number of hops to random destination
  - bisection
    - » minimum number of links that separate the network into two halves
- Warning: these three-dimensional drawings must be mapped onto chips and boards which are essentially two-dimensional media
  - elegant when sketched on the blackboard may look awkward when constructed from chips, cables, boards, and boxes

© Patterson 1994

Important Topologies



Type	Degree	Diameter	Ave Dist	Bisection	N = 1024 Diam	Ave D
1D mesh	≤ 2	N-1	N/3	1		
2D mesh	≤ 4	$2(N^{1/2} - 1)$	$2N^{1/2} / 3$	$N^{1/2}$	63	21
3D mesh	≤ 6	$3(N^{1/3} - 1)$	$3N^{1/3} / 3$	$N^{2/3}$	~30	~10
nD mesh	$\leq 2n$	$n(N^{1/n} - 1)$	$nN^{1/n} / 3$	$N^{(n-1) / n}$		
($N = k^n$)						
Ring	2	N / 2	N/4	2		
2D torus	4	$N^{1/2}$	$N^{1/2} / 2$	$2N^{1/2}$	32	16
k-ary n-cube	2n	$n(N^{1/n})$	$nN^{1/n}/2$		15	8 (3D)
($N = k^n$)		nk/2	nk/4	$2k^{n-1}$		
Hypercube	n	n = LogN	n/2	N/2	10	5
Cube-Connected Cycles						

© Patterson 1994

Topologies (cont)

Type	Degree	Diameter	Ave Dist	Bisection	N = 1024 Diam	Ave D
2D Tree	3	$2\text{Log}_2 N$	$\sim 2\text{Log}_2 N$	1	20	~20
4D Tree	5	$2\text{Log}_4 N$	$2\text{Log}_4 N - 2/3$	1	10	9.33
kD	k+1	$\text{Log}_k N$				
2D fat tree	4	$\text{Log}_2 N$		N		
2D butterfly	4	$\text{Log}_2 N$		N/2	20	20





CM-5 Thinned Fat Tree

© Patterson 1994

Butterfly

Multistage: nodes at ends, switches in middle





- All paths equal length
- Unique path from any input to any output
- Conflicts

Benes Network



- Routes all permutations w/o conflict
- Notice similarity to Fat Tree
- Randomization is major breakthrough

© Patterson 1994

Multistage Fat Tree



- **Randomly assign packets to different paths on way up spread the load**

© Patterson 1994

Example Networks

Name	Number	Topology	Bits	Clock	Link Bisect.		Year
nCube/ten	1-1024	10-cube	1	10 MHz	1.2	640	1987
iPSC/2	16-128	7-cube	1	16 MHz	2	345	1988
MP-1216	32-512	2D grid	1	25 MHz	3	1,300	1989
Delta	540	2D grid	16	40 MHz	40	640	1991
CM-5	32-2048	fat tree	4	40 MHz	20	10,240	1991
CS-2	32-1024	fat tree	8	70 MHz	50	50,000	1992
Paragon	4-1024	2D grid	16	100 MHz	200	6,400	1992
T3D	16-1024	3D Torus	16	150 MHz	300	19,200	1993

© Patterson 1994

Connection based vs. Connectionless

- Telephone: operator sets up connection between the caller and the receiver
  - once the connection was established, conversation could continue for hours
- Share transmission lines over long distances by using switches to multiplex several conversations on the same lines
  - " time division multiplexing" divide BW transmission line into a fixed number of slots, with each slot assigned to a conversation
- Problem: lines busy based on number of conversations, not amount of information sent
- connectionless: every package of information must have an address => packets
  - Each package is routed to the destination by looking at its address e.g., the postal system
  - Split phase buses are send packets

© Patterson 1994

Packet formats



- **Fields: Destination, Checksum(C), Length(L), Type(T)**
- **Data/Header Sizes in bytes: (4 to 20)/4, (0 to 1500)/26, 48/5**

© Patterson 1994

Congestion Control

- **Packet switched networks do not reserve BW=> contention**
- **Solution: prevent oackers from entering until contention is reduced (metering lights)**
- **Options:**
  - **packet discarding: If a packet arrives at a switch and there is no room in the buffer, the packet is discarded**
  - **flow control: between pairs of receivers and senders; use feedback to tell the sender when it is allowed to send the next packet**
    - » **back-pressure: seaprate wires to tell to stop**
    - » **window: give the original sender the right to send N packets before getting permission to send more (overlap the latency of the interconnection with the overhead to send and receive a packet)**
  - **choke packets: Each packet received by busy switch in warning state sent back to the source via choke packet. Source reduces traffic to that destination by a fixed %.**

© Patterson 1994

Store and Forward vs. Cut-Through

- store-and-forward policy: each switch waits for the full packet to arrive in the switch before it is sent on to the next switch
- cut through routing or worm hole routing: switch examines the header, decides where to send the message, and then starts forwarding it immediately.
  - In worm hole routing when the head of the message is blocked the message stays strung out over the network, potentially blocking other messages. (needs only buffer the piece of the packet that is sent between switches) CM-5 uses it, with each switch buffer being 4 bits per port.
  - Cut through routing lets the tail continue when the head is blocked, accordioning the whole message into a single switch. (requires a buffer large enough to hold the largest packet)
- Advantage: latency reduces from function of number of intermediate switches X by the size of the packet vs. time for 1st part of the packet to negotiate the switches + the packet size ÷ interconnect BW

© Patterson 1994

Switching

w = wire width (flit)
m = message size
b = m/w
H = number of hops
R = delay per router

- Circuit switching
  - establish end-to-end route, then transmit data
  - $L = HR_c + b$
- Packet switching
  - route data as it moves forward
  - store-and-forward: $L = H(b + R_{sf})$
  - cut-through: $L = HR_{ct} + b$
  - typically, $R_{ct} = 32/W$
  - most modern networks are about 1 small packet deep

© Patterson 1994

Examples

Machine	Network	W	R	rate MHz	MB/s per link
nCUBE/2	13-D hypercube	1	40	40	2.2
CM-5	4-D Thinned Fat Tree	4	8	40	20
Delta	2-D Mesh	8	2	~40	40
T3D	3-D Torus	16	?	150	300

- Generally, topologies with larger distance have better physical layout, so they have shorter, wider links and smaller routing delays. Hence, latencies are similar.
  - $L = HR_{ct} + M/w$
- What about bandwidth.
  - low degree networks have few links per processor
  - if each message travels a large number of links
    => few outstanding messages per processor
    (similar to bisection bandwidth)
  - with skinny wires, message occupies path for a long time

© Patterson 1994

Routing

- Deterministic - follows a pre-specified route
  - mesh: dimension-order routing
    - » $(x_1, y_1) \rightarrow (x_2, y_2)$
    - » first $\Delta x = x_2 - x_1$,
    - » then $\Delta y = y_2 - y_1$,
  - hypercube: e-cube routing
    - » $X = x_o x_1 x_2 \ldots x_n \rightarrow Y = y_o y_1 y_2 \ldots y_n$
    - » R = X xor Y
    - » Traverse dimensions of differing address in order
  - tree: common ancestor
- Adaptive - route based on network state (e.g. contention)
- Deadlock free





© Patterson 1994

Practical Issues

Interconnect	*MPP*	*LAN*	*WAN*
Example	CM-5	Ethernet	ATM
Standard	No	Yes	Yes
Fault tolerance?	No	Yes	Yes
Hot Insert?	No	Yes	Yes

- **Standards: no choice for WAN, LAN**
- **Fault Tolerance: Can nodes fail and still deliver messages to other nodes? no choice for WAN, LAN**
- **Hot insert: If the interconnection can survive a failure, can it also continue operation while a new node is added to the interconnection? no choice for WAN, LAN**

© Patterson 1994

Protocols: the HW/SW interface

- **Internetworking: allows computers on independent & incompatible networks to communicate reliably & efficiently**
  - **enabling technologies: SW standards that allow reliable communication without reliable networks**
  - **hierarchy of layers, giving each layer responsibility for a portion of the overall communication task, called protocol families or protocol suites**
- **Transmission Control Protocol/Internet Protocol (TCP/IP) This protocol family is the basis of the Internet**

© Patterson 1994

Protocol



- key to protocol families is that communication occurs logically at the same level of the protocol, called peer-to-peer, but it is implemented via services of the lower level
- Danger is each level increases latency

© Patterson 1994

TCP/IP Headers



- IP at bottom, TCP above
- 20B headers standard

© Patterson 1994

FTP from Stanford to Berkeley



- **BARRNet is a WAN for Bay Area**
- **T1 is 1.5 Mbit/s leased line; T3 is 45 Mbit/sec; FDDI is 100 Mbit/sec LAN**
- **IP sets up connection, TCP sends file**

© Patterson 1994

Summary: Interconnections

- **Communication between computers**
- **Packets for standards, protocols to cover normal and abnormal events**
- **Implementation issues: length, width, media**
- **Performance issues: overhead, latency, bisection BW**
- **Topologies: many to chose from, but (SW) overheads make them look the alike; cost issues in topologies**

© Patterson 1994