CS252
Graduate Computer Architecture
Lecture 6

Tomasulo Scheduling for Out-Of-Order Execution

September 20, 2000

Prof. John Kubiatowicz

Review: Exceptions and Compiler Scheduling

- Careful compiler scheduling can remove stalls and speed up code. Dependencies must be maintained.
  - Dependence: intended flow of data from instruction to instruction. First instruction writes data to register, second reads it.
  - Anti-Dependence: reuse of register name - no flow of information! First instruction reads register, then second instruction writes it
  - Output-Dependence: reuse of register name - no flow of information! First instruction writes register, then second instruction writes it

  Compiler must respect dependencies, schedule to avoid stall from RAW hazards.
- Loop unrolling:
  - multiple iterations per loop - all instructions from all iterations
  - Involves compiler-based register renaming
- Software pipelining:
  - multiple iterations per loop - one instruction from each iteration
  - Turns Dependencies into Anti-Dependencies!
  - Often used for floating-point which has long latencies.

Review: Issues with general Scheduling

- How do we prevent WAR and WAW hazards?
- How do we deal with variable latency?
  - Forwarding for RAW hazards harder.

Instruction		Clock Cycle Number																
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17
LD	F6,34(R2)	IF	ID	EX	MEM	WB												
LD	F2,45(R3)		IF	ID	EX	MEM	WB											
MULTD	F0,F2,F4			IF	ID	stall	M1	M2	M3	M4	M5	M6	M7	M8	M9	M10	MEM	WB
SUBD	F8,F6,F2				IF	ID	A1	A2	MEM	WB								
DIVD	F10,F0,F6					IF	ID	stall	stall	stall	stall	stall	stall	stall	stall	stall	D1	D2
ADDD	F6,F8,F2						IF	ID	A1	A2	MEM	WB						

RAW

WAR

Review: Scoreboard from CDC 6600

- Scoreboard (ala CDC 6600 in 1963)
  - Centralized control structure
  - Many independent functional units (not necessarily pipelined)
- Key idea of Scoreboard: Allow instructions behind stall to proceed (Decode => Issue instr & read operands)
  - Enables out-of-order execution => out-of-order completion
  - Original version didn't handle forwarding.
  - No automatic register renaming
  - Pipeline stalls for WAR and WAW hazards.
  - Are these fundamental limitations???

Review: Scoreboard Architecture (CDC 6600)



Review: Four Stages of Scoreboard Control

- Issue—decode instructions & check for structural hazards (ID1)
  - Instructions issued in program order (for hazard checking)
  - Don't issue if structural hazard
  - Don't issue if instruction is output dependent on any previously issued but uncompleted instruction (no WAW hazards)
- Read operands—wait until no data hazards, then read operands (ID2)
  - All real dependencies (RAW hazards) resolved in this stage, since we wait for instructions to write back data.
  - No forwarding of data in this model!

Review: Four Stages of Scoreboard Control

- Execution—operate on operands (EX)
  - The functional unit begins execution upon receiving operands. When the result is ready, it notifies the scoreboard that it has completed execution.
- Write result—finish execution (WB)
  - Stall until no WAR hazards with previous instructions:

Example:

```
DIVD   F0,F2,F4
ADDD   F10,F0,F8
SUBD   F8,F8,F14
```

CDC 6600 scoreboard would stall SUBD until ADDD reads operands

Another Dynamic Algorithm: Tomasulo's Algorithm

- For IBM 360/91 about 3 years after CDC 6600 (1966)
- Goal: High Performance without special compilers
- Differences between IBM 360 & CDC 6600 ISA
  - IBM has only 2 register specifiers/instr vs. 3 in CDC 6600
  - IBM has 4 FP registers vs. 8 in CDC 6600
  - IBM has memory-register ops
- Small number of floating point registers prevented interesting compiler scheduling of operations
  - This led Tomasulo to try to figure out how to get more effective registers — renaming in hardware!
- Why Study? The descendants of this have flourished!
  - Alpha 21264, HP 8000, MIPS 10000, Pentium II, PowerPC 604, …

Tomasulo Algorithm vs. Scoreboard

- Control & buffers distributed with Function Units (FU) vs. centralized in scoreboard;
  - FU buffers called "reservation stations"; have pending operands
- Registers in instructions replaced by values or pointers to reservation stations(RS); called register renaming ;
  - avoids WAR, WAW hazards
  - More reservation stations than registers, so can do optimizations compilers can't
- Results to FU from RS, not through registers, over Common Data Bus that broadcasts results to all FUs
- Load and Stores treated as FUs with RSs as well
- Integer instructions can go past branches, allowing FP ops beyond basic block in FP queue

Tomasulo Organization



Reservation Station Components

Op: Operation to perform in the unit (e.g., + or –)

Vj, Vk: Value of Source operands
- Store buffers has V field, result to be stored

Qj, Qk: Reservation stations producing source registers (value to be written)
- Note: No ready flags as in Scoreboard; Qj,Qk=0 => ready
- Store buffers only have Qi for RS producing result

Busy: Indicates reservation station or FU is busy

Register result status—Indicates which functional unit will write each register, if one exists. Blank when no pending instructions that will write that register.

Three Stages of Tomasulo Algorithm

1. Issue—get instruction from FP Op Queue
   If reservation station free (no structural hazard), control issues instr & sends operands (renames registers).
2. Execute—operate on operands (EX)
   When both operands ready then execute; if not ready, watch Common Data Bus for result
3. Write result—finish execution (WB)
   Write on Common Data Bus to all awaiting units; mark reservation station available

- Normal data bus: data + destination ("go to" bus)
- Common data bus: data + source ("come from" bus)
  - 64 bits of data + 4 bits of Functional Unit source address
  - Write if matches expected Functional Unit (produces result)
  - Does the broadcast

Tomasulo Example

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2			
LD	F2	45+	R3			
MULTD	F0	F2	F4			
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
	Mult2	No					

Register result status:

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
0	FU								

Tomasulo Example Cycle 1

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1		
LD	F2	45+	R3			
MULTD	F0	F2	F4			
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	Yes	34+R2
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
	Mult2	No					

Register result status:

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
1	FU			Load1					

Tomasulo Example Cycle 2

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1		
LD	F2	45+	R3	2		
MULTD	F0	F2	F4			
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	Yes	34+R2
Load2	Yes	45+R3
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
	Mult2	No					

Register result status:

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
2	FU	Load2		Load1					

Note: Unlike 6600, can have multiple loads outstanding

Tomasulo Example Cycle 3

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	
LD	F2	45+	R3	2		
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	Yes	34+R2
Load2	Yes	45+R3
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	MULTD		R(F4)	Load2	
	Mult2	No					

Register result status:

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
3	FU	Mult1	Load2		Load1				

- Note: registers names are removed ("renamed") in Reservation Stations; MULT issued vs. scoreboard
- Load1 completing; what is waiting for Load1?

Tomasulo Example Cycle 4

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	Yes	45+R3
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	Yes	SUBD	M(A1)			Load2
	Add2	No					
	Add3	No					
	Mult1	Yes	MULTD		R(F4)	Load2	
	Mult2	No					

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
4	FU	Mult1	Load2		M(A1)	Add1				

- Load2 completing; what is waiting for Load1?

Tomasulo Example Cycle 5

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
2	Add1	Yes	SUBD	M(A1)	M(A2)		
	Add2	No					
	Add3	No					
10	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
5	FU	Mult1	M(A2)		M(A1)	Add1	Mult2			

Tomasulo Example Cycle 6

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
1	Add1	Yes	SUBD	M(A1)	M(A2)		
	Add2	Yes	ADDD		M(A2)	Add1	
	Add3	No					
9	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
6	FU	Mult1	M(A2)		Add2	Add1	Mult2			

- Issue ADDD here vs. scoreboard?

Tomasulo Example Cycle 7

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
0	Add1	Yes	SUBD	M(A1)	M(A2)		
	Add2	Yes	ADDD		M(A2)	Add1	
	Add3	No					
8	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
7	FU	Mult1	M(A2)		Add2	Add1	Mult2			

- Add1 completing; what is waiting for it?

Tomasulo Example Cycle 8

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
2	Add2	Yes	ADDD	(M-M)	M(A2)		
	Add3	No					
7	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
8	*FU*	Mult1	M(A2)		Add2	(M-M)	Mult2			

Tomasulo Example Cycle 9

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
1	Add2	Yes	ADDD	(M-M)	M(A2)		
	Add3	No					
6	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
9	*FU*	Mult1	M(A2)		Add2	(M-M)	Mult2			

Tomasulo Example Cycle 10

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
0	Add2	Yes	ADDD	(M-M)	M(A2)		
	Add3	No					
5	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
10	*FU*	Mult1	M(A2)		Add2	(M-M)	Mult2			

- Add2 completing; what is waiting for it?

Tomasulo Example Cycle 11

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
4	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
11	*FU*	Mult1	M(A2)		(M-M+M	(M-M)	Mult2			

- Write result of ADDD here vs. scoreboard?
- All quick instructions complete in this cycle!

Tomasulo Example Cycle 12

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
3	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
12	FU	Mult1	M(A2)		(M-M+M	(M-M)	Mult2			

Tomasulo Example Cycle 13

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
2	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
13	FU	Mult1	M(A2)		(M-M+M	(M-M)	Mult2			

Tomasulo Example Cycle 14

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3		
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
1	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
14	FU	Mult1	M(A2)		(M-M+M	(M-M)	Mult2			

Tomasulo Example Cycle 15

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3	15	
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
0	Mult1	Yes	MULTD	M(A2)	R(F4)		
	Mult2	Yes	DIVD		M(A1)	Mult1	

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
15	FU	Mult1	M(A2)		(M-M+M	(M-M)	Mult2			

Tomasulo Example Cycle 16

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3	15	16
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
40	Mult2	Yes	DIVD	M*F4	M(A1)		

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
16	*FU*	M*F4	M(A2)		(M-M+M	(M-M)	Mult2			

Faster than light computation (skip a couple of cycles)

Tomasulo Example Cycle 55

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3	15	16
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
1	Mult2	Yes	DIVD	M*F4	M(A1)		

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
55	*FU*	M*F4	M(A2)		(M-M+M	(M-M)	Mult2			

Tomasulo Example Cycle 56

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3	15	16
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5	56	
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
0	Mult2	Yes	DIVD	M*F4	M(A1)		

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
56	*FU*	M*F4	M(A2)		(M-M+M	(M-M)	Mult2			

- Mult2 is completing; what is waiting for it?

Tomasulo Example Cycle 57

Instruction status:

Instruction		j	k	Issue	Exec Comp	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	4	5
MULTD	F0	F2	F4	3	15	16
SUBD	F8	F6	F2	4	7	8
DIVD	F10	F0	F6	5	56	57
ADDD	F6	F8	F2	6	10	11

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations:

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	No					
	Mult2	Yes	DIVD	M*F4	M(A1)		

Register result status:

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
56	FU	M*F4	M(A2)		(M-M+M(M-M)		Result			

- Once again: In-order issue, out-of-order execution and completion.

Compare to Scoreboard Cycle 62

Instruction status:

Instruction		j	k	Issue	Read Oper	Exec Comp	Write Result
LD	F6	34+	R2	1	2	3	4
LD	F2	45+	R3	5	6	7	8
MULTD	F0	F2	F4	6	9	19	20
SUBD	F8	F6	F2	7	9	11	12
DIVD	F10	F0	F6	8	21	61	62
ADDD	F6	F8	F2	13	14	16	22

Issue	Exec Comp	Write Result
1	3	4
2	4	5
3	15	16
4	7	8
5	56	57
6	10	11

- Why take longer on scoreboard/6600?
  - Structural Hazards
  - Lack of forwarding

Tomasulo v. Scoreboard (IBM 360/91 v. CDC 6600)

Pipelined Functional Units (6 load, 3 store, 3 +, 2 x/÷)	Multiple Functional Units (1 load/store, 1 + , 2 x, 1 ÷)
window size: ≤ 14 instructions	≤ 5 instructions
No issue on structural hazard	same
WAR: renaming avoids	stall completion
WAW: renaming avoids	stall issue
Broadcast results from FU	Write/read registers
Control: reservation stations	central scoreboard

Tomasulo Drawbacks

- Complexity
  - delays of 360/91, MIPS 10000, IBM 620?
- Many associative stores (CDB) at high speed
- Performance limited by Common Data Bus
  - Each CDB must go to multiple functional units ⇒high capacitance, high wiring density
  - Number of functional units that can complete per cycle limited to one!
    - » Multiple CDBs ⇒ more FU logic for parallel assoc stores
- Non-precise interrupts!
  - We will address this later

CS 252 Administrivia

- Check Class List and Telebears and make sure that you are (1) in the class and (2) officially registered.
- Textbook Reading for Lectures 6 to 8
  - Computer Architecture: A Quantitative Approach, Chapter 4, Appendix B
- Assignment from book coming up soon….

Tomasulo Loop Example

```
Loop: LD     F0   0    R1
      MULTD  F4   F0   F2
      SD     F4   0    R1
      SUBI   R1   R1   #8
      BNEZ   R1   Loop
```

- Assume Multiply takes 4 clocks
- Assume first load takes 8 clocks (cache miss), second load takes 1 clock (hit)
- To be clear, will show clocks for SUBI, BNEZ
- Reality: integer instructions ahead

Loop Example

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1		
1	MULTD	F4	F0	F2		
1	SD	F4	0	R1		
2	LD	F0	0	R1		
2	MULTD	F4	F0	F2		
2	SD	F4	0	R1		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
	Mult1	No						SUBI	R1	R1	#8
	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
0	80	Fu									

Loop Example Cycle 1

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	
1	MULTD	F4	F0	F2		
1	SD	F4	0	R1		
2	LD	F0	0	R1		
2	MULTD	F4	F0	F2		
2	SD	F4	0	R1		

	Busy	Addr	Fu
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
	Mult1	No						SUBI	R1	R1	#8
	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
1	80	Fu	Load1								

Loop Example Cycle 2

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1			
2	LD	F0	0	R1			
2	MULTD	F4	F0	F2			
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F4)	Load1	
	Mult2	No					

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
2	80	Fu	Load1		Mult1						

Loop Example Cycle 3

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1			
2	MULTD	F4	F0	F2			
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F4)	Load1	
	Mult2	No					

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
3	80	Fu	Load1		Mult1						

- Implicit renaming sets up "DataFlow" graph

Loop Example Cycle 4

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1			
2	MULTD	F4	F0	F2			
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F4)	Load1	
	Mult2	No					

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
4	80	Fu	Load1		Mult1						

- Dispatching SUBI Instruction

Loop Example Cycle 5

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1			
2	MULTD	F4	F0	F2			
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F4)	Load1	
	Mult2	No					

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
5	72	Fu	Load1		Mult1						

- And, BNEZ instruction

Loop Example Cycle 6

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6		
2	MULTD	F4	F0	F2			
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F4)	Load1	
	Mult2	No					

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
6	72	Fu	Load2		Mult1						

- Notice that F0 never sees Load from location 80

Loop Example Cycle 7

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6		
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1			

	Busy	Addr	Fu
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load1	
	Mult2	Yes	Multd		R(F2)	Load2	

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
7	72	Fu	Load2		Mult2						

- Register file completely detached from computation
- First and Second iteration completely overlapped

Loop Example Cycle 8

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1		
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6		
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load1	
	Mult2	Yes	Multd		R(F2)	Load2	

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
8	72	Fu	Load2		Mult2						

Loop Example Cycle 9

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6		
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load1	
	Mult2	Yes	Multd		R(F2)	Load2	

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
9	72	Fu	Load2		Mult2						

- Load1 completing: who is waiting?
- Note: Dispatching SUBI

Loop Example Cycle 10

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6	10	
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
4	Mult1	Yes	Multd	M[80]	R(F2)		
	Mult2	Yes	Multd		R(F2)	Load2	

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
10	64	Fu	Load2		Mult2						

- Load2 completing: who is waiting?
- Note: Dispatching BNEZ

Loop Example Cycle 11

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
3	Mult1	Yes	Multd	M[80]	R(F2)		
4	Mult2	Yes	Multd	M[72]	R(F2)		

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
11	64	Fu	Load3		Mult2						

- Next load in sequence

Loop Example Cycle 12

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
2	Mult1	Yes	Multd	M[80]	R(F2)		
3	Mult2	Yes	Multd	M[72]	R(F2)		

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
12	64	Fu	Load3		Mult2						

- Why not issue third multiply?

Loop Example Cycle 13

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2		
1	SD	F4	0	R1	3		
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7		
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
1	Mult1	Yes	Multd	M[80]	R(F2)		
2	Mult2	Yes	Multd	M[72]	R(F2)		

Code:			
LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
13	64	Fu	Load3		Mult2						

Loop Example Cycle 14

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD F0	0	R1	1	9	10
1	MULTD F4	F0	F2	2	14	
1	SD F4	0	R1	3		
2	LD F0	0	R1	6	10	11
2	MULTD F4	F0	F2	7		
2	SD F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
0	Mult1	Yes	Multd	M[80]	R(F2)			SUBI	R1	R1	#8
1	Mult2	Yes	Multd	M[72]	R(F2)			BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
14	64	Fu	Load3		Mult2						

- Mult1 completing. Who is waiting?

Loop Example Cycle 15

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD F0	0	R1	1	9	10
1	MULTD F4	F0	F2	2	14	15
1	SD F4	0	R1	3		
2	LD F0	0	R1	6	10	11
2	MULTD F4	F0	F2	7	15	
2	SD F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	[80]*R2
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
	Mult1	No						SUBI	R1	R1	#8
0	Mult2	Yes	Multd	M[72]	R(F2)			BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
15	64	Fu	Load3		Mult2						

- Mult2 completing. Who is waiting?

Loop Example Cycle 16

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD F0	0	R1	1	9	10
1	MULTD F4	F0	F2	2	14	15
1	SD F4	0	R1	3		
2	LD F0	0	R1	6	10	11
2	MULTD F4	F0	F2	7	15	16
2	SD F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	[80]*R2
Store2	Yes	72	[72]*R2
Store3	No		

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
	Mult1	Yes	Multd		R(F2)	Load3		SUBI	R1	R1	#8
	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
16	64	Fu	Load3		Mult1						

Loop Example Cycle 17

Instruction status:

ITER	Instruction	j	k	Issue	Exec Comp	Write Result
1	LD F0	0	R1	1	9	10
1	MULTD F4	F0	F2	2	14	15
1	SD F4	0	R1	3		
2	LD F0	0	R1	6	10	11
2	MULTD F4	F0	F2	7	15	16
2	SD F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	[80]*R2
Store2	Yes	72	[72]*R2
Store3	Yes	64	Mult1

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk	Code:			
	Add1	No						LD	F0	0	R1
	Add2	No						MULTD	F4	F0	F2
	Add3	No						SD	F4	0	R1
	Mult1	Yes	Multd		R(F2)	Load3		SUBI	R1	R1	#8
	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
17	64	Fu	Load3		Mult1						

Loop Example Cycle 18

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2	14	15
1	SD	F4	0	R1	3	18	
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7	15	16
2	SD	F4	0	R1	8		

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	[80]*R2
Store2	Yes	72	[72]*R2
Store3	Yes	64	Mult1

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load3	
	Mult2	No					

Code:

LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
18	64	Fu	Load3		Mult1						

Loop Example Cycle 19

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2	14	15
1	SD	F4	0	R1	3	18	19
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7	15	16
2	SD	F4	0	R1	8	19	

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	No		
Store2	Yes	72	[72]*R2
Store3	Yes	64	Mult1

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load3	
	Mult2	No					

Code:

LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
19	64	Fu	Load3		Mult1						

Loop Example Cycle 20

Instruction status:

ITER	Instruction		j	k	Issue	Exec Comp	Write Result
1	LD	F0	0	R1	1	9	10
1	MULTD	F4	F0	F2	2	14	15
1	SD	F4	0	R1	3	18	19
2	LD	F0	0	R1	6	10	11
2	MULTD	F4	F0	F2	7	15	16
2	SD	F4	0	R1	8	19	20

	Busy	Addr	Fu
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	No		
Store2	No		
Store3	Yes	64	Mult1

Reservation Stations:

Time	Name	Busy	Op	Vj	S1 Vk	S2 Qj	RS Qk
	Add1	No					
	Add2	No					
	Add3	No					
	Mult1	Yes	Multd		R(F2)	Load3	
	Mult2	No					

Code:

LD	F0	0	R1
MULTD	F4	F0	F2
SD	F4	0	R1
SUBI	R1	R1	#8
BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
20	64	Fu	Load3		Mult1						

Why can Tomasulo overlap iterations of loops?

- **Register renaming**
  - Multiple iterations use different physical destinations for registers (dynamic loop unrolling).
- **Reservation stations**
  - Permit instruction issue to advance past integer control flow operations
  - Also buffer old values of registers - totally avoiding the WAR stall that we saw in the scoreboard.
- **Other idea: Tomasulo building "DataFlow" graph on the fly.**

Data-Flow Architectures

- Basic Idea: Hardware respresents direct encoding of compiler dataflow graphs:

```
Input: a,b
   y:= (a+b)/x
   x:= (a*(a+b))+b
output: y,x
```



- Data flows along arcs in "Tokens".
- When two tokens arrive at compute box, box "fires" and produces new token.
- Split operations produce copies of tokens

Paper by Dennis and Misunas



"Reservation Station?"

Brief, In-class discussion of Monsoon

What about Precise Interrupts?

- Both Scoreboard and Tomasulo have:

  In-order issue, out-of-order execution, and out-of-order completion

- Need to "fix" the out-of-order completion aspect so that we can find precise breakpoint in instruction stream.

Relationship between precise interrupts and speculation:

- Speculation is a form of guessing.
- Important for branch prediction:
  - Need to "take our best shot" at predicting branch direction.
  - If we issue multiple instructions per cycle, lose lots of potential instructions otherwise:
    - » Consider 4 instructions per cycle
    - » If take single cycle to decide on branch, waste from 4 - 7 instruction slots!
- If we speculate and are wrong, need to back up and restart execution to point at which we predicted incorrectly:
  - This is exactly same as precise exceptions!
- Technique for both precise interrupts/exceptions and speculation: *in-order completion or commit*

HW support for precise interrupts

- Need HW buffer for results of uncommitted instructions: *reorder buffer*
  - 3 fields: instr, destination, value
  - Reorder buffer can be operand source => more registers like RS
  - Use reorder buffer number instead of reservation station when execution completes
  - Supplies operands between execution complete & commit
  - Once operand commits, result is put into register
  - Instructions commit
  - As a result, easy to undo speculated instructions on mispredicted branches or on exceptions



Four Steps of Speculative Tomasulo Algorithm

1. Issue—get instruction from FP Op Queue

   If reservation station and reorder buffer slot free, issue instr & send operands & reorder buffer no. for destination (this stage sometimes called "dispatch")

2. Execution—operate on operands (EX)

   When both operands ready then execute; if not ready, watch CDB for result; when both in reservation station, execute; checks RAW (sometimes called "issue")

3. Write result—finish execution (WB)

   Write on Common Data Bus to all awaiting FUs & reorder buffer; mark reservation station available.

4. Commit—update register with reorder result

   When instr. at head of reorder buffer & result present, update register with result (or store to memory) and remove instr from reorder buffer. Mispredicted branch flushes reorder buffer (sometimes called "graduation")

What are the hardware complexities with reorder buffer (ROB)?



- How do you find the latest version of a register?
  - As specified by Smith paper, need associative comparison network
  - Could use future file or just use the register result status buffer to track which specific reorder buffer has received the value
- Need as many ports on ROB as register file

Summary #1

- Reservations stations: *implicit register renaming* to larger set of registers + buffering source operands
  - Prevents registers as bottleneck
  - Avoids WAR, WAW hazards of Scoreboard
  - Allows loop unrolling in HW
- Not limited to basic blocks (integer units gets ahead, beyond branches)
- Helps cache misses as well
- Lasting Contributions
  - Dynamic scheduling
  - Register renaming
  - Load/store disambiguation
- 360/91 descendants are Pentium II; PowerPC 604; MIPS R10000; HP-PA 8000; Alpha 21264