Lecture 10: Case Study—CDC 6600 Scoreboard

Professor Randy H. Katz
Computer Science 252
Spring 1996

Review: Summary

- **Instruction Level Parallelism in SW or HW**
- **Loop level parallelism is easiest to see**
- **SW parallelism dependencies defined for program, hazards if HW cannot resolve dependencies**
- **SW dependencies/Compiler sophistication determine if compiler can unroll loops**
  - **Memory dependencies hardest to determine**

Review: FP Loop Showing Stalls

```
1 Loop: LD    F0,0(R1)   ;F0=vector element
2       stall
3       ADDD  F4,F0,F2   ;add scalar in F2
4       stall
5       stall
6       SD    0(R1),F4   ;store result
7       SUBI  R1,R1,8    ;decrement pointer 8B (DW)
8       BNEZ  R1,Loop    ;branch R1!=zero
9       stall            ;delayed branch slot
```

Rewrite code to minimize stalls?

Instruction producing result	*Instruction using result*	*Latency in clock cycles*
FP ALU op	Another FP ALU op	3
FP ALU op	Store double	2
Load double	FP ALU op	1

Review: Unrolled Loop That Minimizes Stalls

```
1 Loop: LD     F0,0(R1)
2       LD     F6,-8(R1)
3       LD     F10,-16(R1)
4       LD     F14,-24(R1)
5       ADDD   F4,F0,F2
6       ADDD   F8,F6,F2
7       ADDD   F12,F10,F2
8       ADDD   F16,F14,F2
9       SD     0(R1),F4
10      SD     -8(R1),F8
11      SD     -16(R1),F12
12      SUBI   R1,R1,#32
13      BNEZ   R1,LOOP
14      SD     8(R1),F16    ; 8-32 = -24
```

- What assumptions made when moved code?
  - OK to move store past SUBI even though changes register
  - OK to move loads before stores: get right data?
  - When is it safe for compiler to do such changes?

14 clock cycles, or 3.5 per iteration

HW Schemes: Instruction Parallelism

- Why in HW at run time?
  - Works when can't know dependence at run time
  - Compiler simpler
  - Code for one machine runs well on another
- Key idea: Allow instructions behind stall to proceed

```
DIVD  F0,F2,F4
ADDD  F10,F0,F8
SUBD  F8,F8,F14
```

  - Enables out-of-order execution => out-of-order completion
  - ID stage checked both for structural & data dependencies

HW Schemes: Instruction Parallelism

- Out-of-order execution divides ID stage:
  1. Issue—decode instructions, check for structural hazards
  2. Read operands—wait until no data hazards, then read operands
- Scoreboards allow instruction to execute whenever 1 & 2 hold, not waiting for prior instructions

Scoreboard Implications

- Out-of-order completion => WAR, WAW hazards?
- Solutions for WAR
  - Queue both the operation and copies of its operands
  - Read registers only during Read Operands stage
- For WAW, must detect hazard: stall until other completes
- Need to have multiple instructions in execution phase => multiple execution units or pipelined execution units
- Scoreboard keeps track of dependencies, state or operations
- Scoreboard replaces ID, EX, WB with 4 stages

RHK.SP96 7

Four Stages of Scoreboard Control

1. **Issue**—decode instructions & check for structural hazards (ID1)

   If a functional unit for the instruction is free and no other active instruction has the same destination register (WAW), the scoreboard issues the instruction to the functional unit and updates its internal data structure. If a structural or WAW hazard exists, then the instruction issue stalls, and no further instructions will issue until these hazards are cleared.

2. **Read operands**—wait until no data hazards, then read operands (ID2)

   A source operand is available if no earlier issued active instruction is going to write it, or if the register containing the operand is being written by a currently active functional unit. When the source operands are available, the scoreboard tells the functional unit to proceed to read the operands from the registers and begin execution. The scoreboard resolves RAW hazards dynamically in this step, and instructions may be sent into execution out of order.

RHK.SP96 8

Four Stages of Scoreboard Control

3. **Execution**—operate on operands (EX)

   The functional unit begins execution upon receiving operands. When the result is ready, it notifies the scoreboard that it has completed execution.

4. **Write result**—finish execution (WB)

   Once the scoreboard is aware that the functional unit has completed execution, the scoreboard checks for WAR hazards. If none, it writes results. If WAR, then it stalls the instruction.

   Example:

   ```
   DIVD   F0,F2,F4
   ADDD   F10,F0,F8
   SUBD   F8,F8,F14
   ```

   CDC 6600 scoreboard would stall SUBD until ADDD reads operands

RHK.SP96 9

Three Parts of the Scoreboard

1. **Instruction status**—which of 4 steps the instruction is in

2. **Functional unit status**—Indicates the state of the functional unit (FU). 9 fields for each functional unit

   - **Busy**—Indicates whether the unit is busy or not
   - **Op**—Operation to perform in the unit (e.g., + or –)
   - **Fi**—Destination register
   - **Fj, Fk**—Source-register numbers
   - **Qj, Qk**—Functional units producing source registers Fj, Fk
   - **Rj, Rk**—Flags indicating when Fj, Fk are ready

3. **Register result status**—Indicates which functional unit will write each register, if one exists. Blank when no pending instructions will write that register

RHK.SP96 10

Detailed Scoreboard Pipeline Control

Instruction status	Wait until	Bookkeeping
Issue	Not busy (FU) and not result(D)	Busy(FU)← yes; Op(FU)← op; Fi(FU)← `D'; Fj(FU)← `S1'; Fk(FU)← `S2'; Qj← Result(`S1'); Qk← Result(`S2'); Rj← not Qj; Rk← not Qk; Result('D')← FU;
Read operands	Rj and Rk	Rj← No; Rk← No
Execution complete	Functional unit done	
Write result	∀f((Fj(f)≠Fi(FU) or Rj(f)=No) & (Fk(f) ≠Fi(FU) or Rk(f)=No))	∀f(if Qj(f)=FU then Rj(f)← Yes); ∀f(if Qk(f)=FU then Rj(f)← Yes); Result(Fi(FU))← 0; Busy(FU)← No

Scoreboard Example

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2				
LD F2	45+	R3				
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	No								
	Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
FU									

Scoreboard Example Cycle 1

Instruction status

Instruction	j	k	Issue	Read operanc	Executi comple	Write Result
LD F6	34+	R2	1			
LD F2	45+	R3				
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
Integer	Yes	Load	F6		R2				Yes
Mult1	No								
Mult2	No								
Add	No								
Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
1 FU				Integer					

Scoreboard Example Cycle 2

Instruction status

Instruction	j	k	Issue	Read operanc	Executi comple	Write Result
LD F6	34+	R2	1	2		
LD F2	45+	R3				
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
Integer	Yes	Load	F6		R2				Yes
Mult1	No								
Mult2	No								
Add	No								
Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
2 FU				Integer					

Scoreboard Example Cycle 3

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	
LD F2	45+	R3				
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	Yes	Load	F6		R2				Yes
	Mult1	No								
	Mult2	No								
	Add	No								
	Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
3	FU				Integer				

Scoreboard Example Cycle 4

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3				
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	Yes	Load	F6		R2				Yes
	Mult1	No								
	Mult2	No								
	Add	No								
	Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
4	FU				Integer				

Scoreboard Example Cycle 5

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5			
MULTI F0	F2	F4				
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	Yes	Load	F2		R3				Yes
	Mult1	No								
	Mult2	No								
	Add	No								
	Divide	No								

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
5	FU		Integer							

Scoreboard Example Cycle 6

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6		
MULTI F0	F2	F4	6			
SUBD F8	F6	F2				
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	Yes	Load	F2		R3				Yes
	Mult1	Yes	Mult	F0	F2	F4	Integer		No	Yes
	Mult2	No								
	Add	No								
	Divide	No								

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
6	FU	Mult1	Integer							

Scoreboard Example Cycle 7

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	
MULTI F0	F2	F4	6			
SUBD F8	F6	F2	7			
DIVD F10	F0	F6				
ADDD F6	F8	F2				

Functional unit status

Time Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
Integer	Yes	Load	F2		R3				Yes
Mult1	Yes	Mult	F0	F2	F4	Integer		No	Yes
Mult2	No								
Add	Yes	Sub	F8	F6	F2		Integer	Yes	No
Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
7 FU	Mult1	Integer			Add				

RHK.SP96 19

Scoreboard Example Cycle 8a

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	
MULTI F0	F2	F4	6			
SUBD F8	F6	F2	7			
DIVD F10	F0	F6	8			
ADDD F6	F8	F2				

Functional unit status

Time Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
Integer	Yes	Load	F2		R3				Yes
Mult1	Yes	Mult	F0	F2	F4	Integer		No	Yes
Mult2	No								
Add	Yes	Sub	F8	F6	F2		Integer	Yes	No
Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
8 FU	Mult1	Integer			Add	Divide			

RHK.SP96 20

Scoreboard Example Cycle 8b

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6			
SUBD F8	F6	F2	7			
DIVD F10	F0	F6	8			
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	Yes	Sub	F8	F6	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
8 FU	Mult1				Add	Divide			

Scoreboard Example Cycle 9

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9		
DIVD F10	F0	F6	8			
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
10	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
2	Add	Yes	Sub	F8	F6	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
9 FU	Mult1				Add	Divide			

Scoreboard Example Cycle 11

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	
DIVD F10	F0	F6	8			
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
8	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
0	Add	Yes	Sub	F8	F6	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
11 FU	Mult1				Add	Divide			

Scoreboard Example Cycle 12

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2				

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
7	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	No								
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
12 FU	Mult1					Divide			

Scoreboard Example Cycle 13

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13			

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
6	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
13 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 14

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14		

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
5	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
2	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
14 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 15

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14		

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
4	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
1	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
15 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 16

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
3	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
0	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
16 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 17

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
2	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
17 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 18

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9		
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
1	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
18 FU	Mult1			Add		Divide			

Scoreboard Example Cycle 19

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
0	Mult1	Yes	Mult	F0	F2	F4			Yes	Yes
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6	Mult1		No	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
19	Mult1			Add		Divide			

RHK.SP96 31

Scoreboard Example Cycle 20

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	20
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8			
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6			Yes	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
20				Add		Divide			

RHK.SP96 32

Scoreboard Example Cycle 21

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	20
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8	21		
ADDD F6	F8	F2	13	14	16	

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	Yes	Add	F6	F8	F2			Yes	Yes
	Divide	Yes	Div	F10	F0	F6			Yes	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
21	FU					Add		Divide		

Scoreboard Example Cycle 22

Instruction status

Instruction	j	k	Issue	Read operand	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	20
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8	21		
ADDD F6	F8	F2	13	14	16	22

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	No								
40	Divide	Yes	Div	F10	F0	F6			Yes	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
22	FU					Divide			

Scoreboard Example Cycle 61

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	20
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8	21	61	
ADDD F6	F8	F2	13	14	16	22

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	No								
0	Divide	Yes	Div	F10	F0	F6			Yes	Yes

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
61	FU						Divide		

Scoreboard Example Cycle 62

Instruction status

Instruction	j	k	Issue	Read operands	Execution complete	Write Result
LD F6	34+	R2	1	2	3	4
LD F2	45+	R3	5	6	7	8
MULTI F0	F2	F4	6	9	19	20
SUBD F8	F6	F2	7	9	11	12
DIVD F10	F0	F6	8	21	61	62
ADDD F6	F8	F2	13	14	16	22

Functional unit status

Time	Name	Busy	Op	dest Fi	S1 Fj	S2 Fk	FU for Qj	FU for Qk	Fj? Rj	Fk? Rk
	Integer	No								
	Mult1	No								
	Mult2	No								
	Add	No								
0	Divide	No								

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
62	FU								

Scoreboard Summary

- **Speedup 1.7 from compiler; 2.5 by hand BUT slow memory (no cache) limits benefit**
- **Limitations of 6600 scoreboard:**
  - **No forwarding hardware**
  - **Limited to instructions in basic block (small *window*)**
  - **Small number of functional units (structural hazards)**
  - **Wait for WAR hazards**
  - **Prevent WAW hazards**